



INSTALLATION & MAINTENANCE MANUAL

DGZ10B / DGZ10C / DGZ10CBR / DGZ10W
SGZ10B / SGZ10C /SGZ10CBR / SGZ10W




Fig. 1

Product code	Cut-out diameter (mm)
DGZ10xxx	60
SGZ10xxx	80

- Remove the terminal block cover
- Connect the luminaire to the mains supply ensuring the correct polarity is observed: L - Live (brown), E - Earth (green/yellow), N - Neutral (blue)
- Secure the mains cable under the cable clamp and refit the terminal cover
- Insert the terminal block bracket into the side of the luminaire (see Fig. 2) and tighten the screw

Fig. 2



- Lift both of the spring clips on the sides of the fitting and push into the ceiling
- Insert a suitable GU10 lamp (max. 50W) using the rubber suction cup provided
- Switch on and check for correct operation

GENERAL

Clean with a soft dry cloth only, do not use aggressive cleaning products or solvents which may damage the product.

This product is dimmable dependent on lamp type.

This product should be recycled in the correct manner when it reaches the end of its life. Check local authorities for where facilities exist.

WARRANTY

This product has a warranty of 1 year from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch code will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

GENERAL INSTRUCTIONS

These instructions should be read carefully and retained after installation by the end user for future reference and maintenance.

These instructions should be used to aid installation of the following products:

DGZ10B / DGZ10C / DGZ10CBR / DGZ10W / SGZ10B / SGZ10C / SGZ10CBR / SGZ10W

SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician
- Please isolate mains prior to installation or maintenance
- Check the total load on the circuit (including when this product is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker
- Please note the IP (Ingress Protection) rating of this luminaire when deciding the location for installation
- Allow 50mm above and around the fitting for air dissipation (do not cover the fitting with insulation)
- This product is for indoor use only
- This product is Class I and must be earthed
- This product is IP20 rated

INSTALLATION

- Provide power to the required point of installation
- Cut a suitable hole in the mounting surface as per the cut-out details (see Fig. 1) ensuring not to infringe with any joists, gas/water pipes or electrical cables

**INTERNATIONAL
CONTACT DETAILS**



**230V
50Hz**

IP20



ML
ACCESSORIES LTD



**UK
CA** **CE**



14

ML Accessories Limited LU5 4LT
www.mlaccessories.co.uk