

# LED LITE™ 21W GALAXY LED - GALAXY 21

## Energy Saving LED IP54 DECORATIVE ROUND BULKHEAD

### 21W GALAXY LED MAINTAINED EMERGENCY LUMINAIRE INSTRUCTIONS

These instructions are in addition to the standard luminaire instructions that were supplied with the product you have purchased. Please read them carefully and install the luminaire as per instructions, then keep the instructions for future reference and maintenance.

#### Important information

It is recommended that luminaires are installed by a qualified electrician ensuring the installation complies to current IEE wiring regulations & local building control.

- These products are designed for connection to a 110-240V mains supply.
- Any broken or damaged parts should be replaced as soon as possible.
- We will not accept responsibility for any claims arising from poor installation.

#### INSTALLATION

1. The luminaire should be installed as per the Instruction sheet supplied.
2. In addition, a secondary permanent live supply should be fed to the luminaire, in line with the switch mains supply. The permanent supply MUST be taken from the same phase as the switch live supply and MUST be wired so that upon test, it is isolated at the same time as the switch supply.
3. Connect the battery supply to the module by joining the connectors, ensuring correct polarity is observed.
5. The green LED fitted to the luminaire should be on after reconnecting the power supply, indicating that the batteries are charging.
6. The batteries should be charged for at least 24 hours before carrying out a full discharge test to check if the maintained duration is being achieved.

#### OPERATION / MAINTENANCE

1. Nominal battery life is 4 years, after which time they should be replaced with a suitable equivalent.
2. When the lamp operates from the battery supply it will be at a reduced light level.
3. Keep the luminaire clean so it will not affect performance.

#### OPERATIONS CHECK

Periodic testing should be carried out monthly by simulating a failure of supply, causing the fitting to be energised from its battery. Interruption of the supply should be carried out by the operation of a local key switch or other isolation device. During this period all fittings should be examined visually to ensure that they are functioning correctly. At the end of the test period the supply should be restored and all indicator lamps or devices checked to ensure that the normal supply has been restored.

The duration of the simulated failure should be:

##### **Each month:**

Isolate the power supply and check the light is illuminated. This test should last for no more than 45 minutes. Complete the test record form supplied.

##### **Every six months:**

Isolate the power supply and check that the light is still illuminated after 1 hour.

##### **Once each year:**

Isolate the power supply and check that the light is still illuminated after 3 hours. Complete the test record form.

# INSTALLATION, MAINTENANCE AND OPERATION CHECK RECORD

Location:

Installation Date:

Installation Test Duration:

Installed By:

Month	Test	Year:		Year:		Year:		Year:		Year:	
		Sign	Date	Sign	Date	Sign	Date	Sign	Date	Sign	Date
1	Short										
2	Short										
3	Short										
4	Short										
5	Short										
6	1 hr Endurance										
7	Short										
8	Short										
9	Short										
10	Short										
11	Short										
12	3 hr Endurance										