

CONCERTO ZIP DOWN LIGHT

Description

The Concerto Zip family of down lights are an internal recessed fitting suitable for display purposes and low glare applications.

Lamp Types,

Single and twin 13/18/26W TCD 2pin and 4pin

Single and twin 32/42W TCT 4pin

Weather rating: IP20

Recessed glass Version IP44

Conforms to: BS EN 60598-2-2

The unit must be wired in accordance with all the latest relevant wiring and building regulations.

Suitable for mounting on normally flammable surfaces.

Location

The Concerto down light luminaire should only be ceiling mounted. The luminaire shall under no circumstances be covered with insulating matting or any other similar material.

Product Diagram



Installation

ISOLATE THE MAINS SUPPLY BEFORE WORKING ON THE INSTALLATION.

1. Plan the position of the luminaries carefully ensuring there are no wires, joists etc behind the mounting position. Cut the recessed hole in the mounting surface (200mm diameter).
2. Remove the drop glass or recessed glass assembly if fitted. Remove the reflector assembly.
3. Pass the incoming mains cable through the grommet into the fitting.
4. Connect the incoming mains cable as follows live to "L" neutral to "N" and earth to "⏏" pass the mains cable through the cable clamp and push the retaining strap to secure in position.
5. Adjust the geartray support by slackening the support bracket screw and moving the bracket to suit.
6. Fit the slider clips to the cage.
7. Carefully feed the cable and the metal body back into the recessed hole making sure no cable is trapped.
8. Holding the luminaire in position, slide down the 3-slider clips to secure the fitting into position.
9. Refit the reflector (one screw).
10. Fit the appropriate lamp(s). Re-fit the recessed or drop glass assembly.
11. Apply the power.

Further Advice

IF IN DOUBT WITH INSTALLATION CONTACT A QUALIFIED ELECTRICIAN.

The manufacturer reserves the right to improve the product specification without prior notice.