APPENDIX I I-DVR.NET REGISTRATION

DDNS Registration on I-DVR.NET

In the package of each DVR, you will find a sticker shows account information including username and password that allows users to login I-DVR.NET for registration.

To register DDNS on I-DVR.NET, please follow the steps as shown.

Step 1. Please open IE browser and then enter "<u>http://i-DVR.NET/logon.asp</u>" in IE browser bar. Next, "Control Panel Logo" dialog will appear. Enter the username and password provided by the sticker and then press, "Logon."





Step 2. After login successfully, enter name at "host" in "Add New Record" dialog. For example, "hostname" is the host name, and then the address will be "hostname.i-dvr.net." Select "Standard" type and enter an IP address of the DVR. Input known IP address if any, or press the "insert" button if none.

Add New Rec	cord					
	host.domain		IP		actions	
	hostname	.i-dvr.net	220.135	105.67	insert	
Please ent For examp Therefore, "hostnam	er any name by you Column, "host.don le, "hostname" IE address will be ne.i-dvr.net"	r choice at nain"		System will computer IF If the DVR the column If not, you	automatically show IP is known, you o can press "insert"	the current can type it in button.

Step 3. The "Host Manager" dialog will show "insert succeed" when user setup successfully. The "host.domain" column will show up the setup just entered. Next, enter the DVR the same time setting the DDNS client machine information If DDNS set up at DVR side successfully, the website will update the IP information in one minute. The IP column will be renewed to the corresponding IP address by pressing "F5: refresh" button.



Step 4. Enter DVR \rightarrow Main Menu \rightarrow Configuration \rightarrow Network Setup \rightarrow DDNS. Activate DDNS functions and input related information.

11 00000 (3000 700)	2011/D3/09 15:	Network	setup	°			3/	9/20	11 PN	1 03:5	7:4
Connected to:		0000000000	00000		_	Ste	ൻിര 🏼 🖻	_	_	D	
	Static IP	PPPo	อโร	-	6	36					
DP8		(192	a	163	a	6	a	61)	
Subnet Mask:		(255	a	255	a	255	a	0)	
Cateway:		(192	a	163	a	6	a	1)	
DNS:		(8		8	a	8		8)	
	DD	NG	IN	hr 🔊		-	Mall	Gast			
		work pro	nerly v	vhe	n this	: or	tion	selec	rted		
🗹 Enabla	DDING		peny v	vine		, 06			cicu.		-
Server			(i-dvr.n	et					~		1
Host:			hostna	me	l-dvr.	ncî					
User:			(ic0000)	01							
Password:			00000	0							
							-				
(OK			Can	cel		\supset				
CH13	CH14			СН	15		ا ا		CH1	6	
							•				
	Thi	s part of	the inf	orn	natio	n re	quir	ed a	nd th	e	
		sar	ne wit	hin	the i	-dv	r.net				

Step 5. Back to the i-dvr.net, on this page by pressing "F5: Refresh", IP will be automatically updated into the DVR of the real IP location.

<u>Host Manager</u>	1			
		Msg: ip update succeed		
	host.domain	ID	actions	
	hostname.i-dvr.net	124.219.25.11	update delete	

APPENDIX II ez-dns REGISTRATION

DDNS Registration on ez-dns.com

In addition to I-DVR.NET the Company, the other has a ez-dns.com server may be used.. To register DDNS on ez-dns.com, please follow the steps as shown.

Step 1. Please open IE browser and then enter "<u>http://ez-dns.com</u>" in IE browser bar. First time, please click on the top of the screen of "Sing up" (red box)

http://ee-disc.com/	v
Sign up 曝? Login	
r Logen	
Control Panel Logon	
User Name:	
Password: Password is case sensitive.	
submit reset	

Step 2. To input a user name and password, after clicking "singup". Later, log in to use ez-dns.com that this group account password

User Name	demodvr	
Password		
Pas	averd is case sensitiv	/e.

Step 3. The "host.domain" column will show up the setup just entered.

Next, enter the DVR the same time setting the DDNS client machine information If DDNS set up at DVR side successfully, the website will update the IP information in 10 minute. The IP column will be renewed to the corresponding IP address by pressing "F5: refresh" button. Sign up 🛪 Host 🛪 Logout

host.domain	IP	actions
demodvr.ez-dns.com	202.132.159.80 124.219.26.209 (now ip)	update
"host.domain" is named by your ch "demodvr.ez-dns.com" is what the server generates	The system will a computer IP, If the DVR's IP Io click update, If DVR IP has any Here at the same And then IP colu to it's real IP Ac	automatically display the current user's cation is known can be input field and y changes, there are updates e time. Press, "F5: Refresh" imn will update automatically Idress.

Step 4. Enter DVR \rightarrow Main Menu \rightarrow Configuration \rightarrow Network Setup \rightarrow DDNS. Activate DDNS functions and input related information.

2011/03/0	09 16:09:25	2011/03/09 16:	72.98GB/7	74 . 52GB		-	n.	3/9	0/20	11-11-P	M 04:0	09:24
			Network	Setup							_	
	Connected to:					1	Ste	tic IP				
		Static IP	PPP	OE		5	36)			
201	IPs			192	a	163	a	6	a	61		
	Subnet Mask:			255	a	255	a	255	a	0		and the second
	Catoway:			192		163	a	6	0	1		TT TT
E.	DNS:			8	-	8	-	8		8		II II
Н												
201	HITTP	DDNS	work prop	erly wh	rp en	this	opti	Maill on se	Sei	JD)	
	Servert			ez-ens								
B	Host:		(damod	Mr.G	w dne	600	ממ				
281	User:		(damod	917							
	Password:		(00000	0							
Ē		OK		(ික	cel						
	CH13	CH14			сн	15		<u>م</u>		СН	16	4
		This part (f tha infa	rmatio	n r/	auir	od -	and t	hod		- with	in th

This part of the information required and the same within the ez-dns.com

Step 5.Back to the ez-dns.com, on this page by pressing "F5: Refresh", IP will be automatically updated into the DVR of the real IP location.

host.domain	ID	actions
demodvr.ez-dns.com	124.219.26.209	update

APPENDIX III Remote Monitoring IE ActiveX Control Installation Instruction

When using IE for remote monitoring for the first time, IE ActiveX Control is needed to be downloaded.

1. When remote monitoring on IE for the first time, an alert message occurs "Install ActiveX control" on the tool bar.

🚈 DVR Remote - Microsoft Internet Explorer		
Eile Edit Yiew Favorites Iools Help		
🔇 Back 🔹 🕘 🔹 🔝 🐔 🔎 Search 🎲 Favorites 🔗 🙆 + 😓 🚍		
This site might require the following ActiveX control: iWatchDVR	Click here to install	
Click here to install the following ActiveX control: '' iWatchE	OVR [*] from	

2. Click at this alert message and select "Install ActiveX Control"

DVR Remote - Microsoft Internet Explorer	
Eile Edit View Favorites Iools Help	
🔇 Back 👻 🕤 👻 📓 🐔 🔎 Search 📩 Favorites 🔗 🖗)• 🕹 🛃
Address 🛃 http://h264demo.i-dvr.net:610/ie.html	•
🗑 This site might require the following ActiveX control: *	Install ActiveX Control
🎯 Click here to install the following ActiveX contro	What's the Risk?
	Information Bar Help

3. "Do you want to install this software" alert pops up. Select "Install".

Windows Explorer - Security Warning		Citeres .	×
Do you want to install this software?			
Name: iWatchDVR Publisher:			
More options	Install	<u>D</u> on't Install	
While files from the Internet can be your computer. Only install software	useful, this file type can p from publishers you trus	ootentially harm t. <u>What's the ris</u>	<u>k?</u>

- 4. After installation, IE remote monitoring image appears.
- 5. If message, "Your security Settings do not allow web sites to use ActiveX controls installed on your computer." pops on when logging in, please follow the next instruction.



6. First select "Tools" on the tool bar and then select "Internet Options"

🚰 DVR Remote - Microso t In	ternet Exp orer		_ 🗆 ×
Eile Edit View Favorites	Tools Hep		-
🔇 Back 🔹 🕥 👻 🔝 🛃	Mail and Jews >	s 🕙 🍰 🗟	
Address 🛃 http://h264demo.i-c	Pop-up Blocker Manage Add-ons	🗾 🔁 Go	Links »
Your security settings do not a options	Synchronize Windows Update	X controls installed on your computer. This page may not display correctly. Click here for	×
	Internet Options		

7. Select Security →Trusted Sites → Sites

Ge	eral Secu elect a Web	rity Privacy Content zon	y Content Content	Connectio s security	ns Program attings.	ms Advanced	
	Internet	Local inti	net Truste	ed sites	Recricted sites		
(Truste This zo trust no data.	ed sites one contains of to damage	Web sites the your compu	iat you ter or		<u>S</u> ites	
٢	Security Jeve	el for this zor	ie ———				
	Cu (stom Custom settir To chan ge To use the	ngs. the settings, recommende	click Custo d settings,	m Level. click Defaul	t Level	
			<u>C</u> ustom L	evel	<u>D</u> efau	It Level	
			OK.		Cancel	Apply	

8. Enter DVR address (This address is only for demonstration. Please use the address depends on the setup of on-site DVR.) into the blanks shown in picture, and then press "add."



	and remove web sites from will use the zone's security :	n this zone. All web sites settings.
d this Web site to t http://h264demo.i-d	the zone: Ivr.net	<u>A</u> dd
eb sites:		
		<u>R</u> emove
		-
Require server ve	rification (https:) for all sit	es in this zone
		Close

9. Newly added website will appear at the trusted web sites list. Press close.
Trusted sites

Add this Web site to the zone:	Jine 3 Securi	ry seconds.	Add
http://h264demo.i-dvr.net]		<u>R</u> emove
Require server verification (ht	tps:) for all	sites in this 2	
<u>C</u> us	tom Level	<u>D</u> e	fault Level

10. Go back to IE window, press refresh button or F5.

