

## DCP917S

### Doorbell wired to wireless converter kit - White

The DCP917S Doorbell wired to wireless converter kit has been designed to work with your existing wired push button. Simply wire it to the push button, then link it with any Honeywell wireless doorbell kit. Place your wireless doorbell anywhere in the home or garden so you'll never miss a visitor.



### Pack Contents:

1 x Wired to Wireless Converter, 1 x CR2032 (3V) Battery, 1 x Quick Start Guide, 1 x Safety & Guarantee, 1 x Declaration of Conformity

### Key Features and Benefits:

**Never miss a visitor or delivery** - Link the converter to any Honeywell wireless doorbell, and thanks to Honeywell ActivLink™ technology providing a reliable wireless range of up to 200m, you'll never miss a visitor or delivery again.

#### Easy To Install -

All Honeywell push buttons and accessories are easy to install, with optional screw-free installation and an easy open battery compartment so you can be set up in minutes. All this is backed up by our 2 year product guarantee.

### Specification:

<b>Wired to Wireless Converter</b>	
Colour	White
Wall mounted	Yes
Frequency / Wireless Range*	868MHz / 200m
Push Fit Connectors	Yes
Power	Battery: 1 x CR2032 (3V) - (included) / Optional external supply (transformer) 8V/12V AC
Battery Life (Years)	2
Battery Features	Low Battery Indicator / Easy Open Battery Compartment
Operating Temperature/Storage Temperature	0°C to +40°C/-20°C to +60°C
Dimensions (mm) / Weight (g)	80 (h) x 64 (w) x 16 (d) / 41 (g)
Fixings	Brackets / Rawl Plugs / Screws

  

<b>Pack</b>	
EAN Code / Standard Pack EAN Code	5004100967541 / 5004100967602
Pack Dimensions (mm) / Weight (g)	137 (h) x 146 (w) x 30 (d) / 140 (g)
Standard Pack Quantity	6

\* Measured in open field conditions, walls, ceilings and metal structures will reduce the maximum range.