

Available finish:- Black

Read these instructions before commencing installation. Please give these instructions to the owner/occupier after installation to retain for future reference/maintenance.

IP65    240V~50Hz 46W max.

These fittings are Class II and do not require an Earth

Important Information



It is recommended that these luminaires are installed and fitted by a qualified electrician ensuring the installation complies with current IEE wiring regulations & local building control. These products are designed for connection to a 240V~50Hz supply. Any faulty, broken or damaged luminaires should be replaced immediately. KSR will not accept responsibility for any claims arising from a poor installation. Please Note: The limited warranty shall be deemed null and void in the following circumstances: Failure by the installer, end user or any third party to exercise caution to protect any covered product or part from outside damage, adverse temperature (normal operating ambient temperature -15 ~ +40°C), humidity conditions, fluctuations in the electrical system or physical abuse as well as failure related to workmanship in the installation of the products or parts.

Important User Advice


Always switch off mains supply before servicing lamp changes and maintenance. Please ensure that a suitable maintenance schedule is performed including greasing any exposed metal parts and cleaning with a non-abrasive cleaner to ensure the product gives you a long lasting trouble free life.

Installation Procedure

- Safely isolate the mains supply before installation.
- Remove the head by loosening the grub screw and twisting anticlockwise.
- Route the cable through the cable gland (8mm-12mm) and terminate wiring as per Figure 1.
- Install suitable lamp not exceeding the maximum wattage.
- Refit the head in reverse of removal ensuring the seal is clean, in place and undamaged, grease the grub screw and tighten.
- Tighten the cable gland ensuring a water tight connection.
- Secure the bollard in place using suitable fixings for the application.
- Turn mains supply on and test luminaire.
- Never touch a hot lamp.




200mm
KSR1180




200mm
KSR1181

Fig.1



Lamp Details

Lamp Cap: E27 GLS
Wattage: 46W (max)



KSR Lighting recommend only branded lamps
For example: Sylvania, GE, Philips or Osram

