



Remote Test, Hush & Locate switch **REMTH**

For fixing to recessed or surface single gang box

Purpose:

Designed to enable remote functionality of connected hard wired Kidde smoke, heat & CO alarms, as below:

- CO- 423/9hi & 423/9hir
 - Slick® Fast Fit- 1SFW/1SFWR, 2SFW/2SFWR, 3SFW/3SFWR
- Kidde Firex- 4870/4881, 4973/4985, 4899/4892

Function and Compatibility:

This is a mains powered (230 vac) device for use with Kidde hard wired smoke, heat & CO alarms as listed above. [A Wireless "RTH" switch is available for use with Slick® alarms.](#)

It is designed to control a single unit or an interlinked group of alarms and may be connected at any part of the supply circuit where the interlink line is present. *It can be retrofitted into existing installations already equipped with Kidde alarms.*

- **Test** all interconnected Alarms
- **Hush** unwanted alarms
- **Locate** the initiating alarm in event of activation
- **Manually trigger interconnected alarms**

Applications:

- 1 Suitable for any householder who would have difficulty reaching an alarm's Test or Hush buttons easily
- 2 Can be retrofitted where occupancy type changes

Features:

The 2 push button switches enable you to remotely test and control Kidde smoke, heat & CO hard wired alarms.

The buttons are marked Test and Hush; T and H are embossed in Brail on each button.

The LED displays red or green dependent on status:

- Mains Healthy - Green
 - Test Status - Flashing red
- Hush\ Locate status - Steady red



Fixings:

2 machine screws (M3.5) supplied for standard single gang socket or dry lining box.



Test Button

Pressing Test Button once - all alarms will operate for 10 seconds - LED changes from Green to Flashing red.
After 10 seconds it resets back to Green

To Test connected Smoke and Heat Alarms for 10 seconds +

Press Test Button for 3 seconds - all sounders will operate continuously for longer than 10 seconds.
LED changes from Green to flashing red.
Press Test button again to silence and reset alarms - *LED reverts to Green*



Hush\ Locate Button

This enables you to locate the initiating alarm when event occurs, and to silence unwanted alarms. Duration of hush is preset to either 8 or 15 minutes duration by the installer and can be manually overridden by the user.

Installation:

This is for installation by a qualified electrician.

Comprehensive installer & user instructions [also available as pdf from web site] included. *Please digest before commencing installation process.*

Up to 24 interconnected smoke & heat alarms can be connected or 18 smoke, heat & CO alarms.

Electrical Rating/Operating Range:

230V AC

4.5 deg C to 37.8.

R Humidity up to 85%

Dimensions:

85mm square x 35

Depth dependent too on mounting type; using surface mount box would add 25 or 32mm depth

Packed in cartons; outers of 6

Kidde Fyrnetics
Mathisen Way, Colnbrook, SL3 0HB
www.smoke-alarms.co.uk
01753 685148 Fax 685096