

with SCART AV Input and F-Aerial Connections

This new compact unit allows you to modulate your DVD/CCTV signal, so that it can be distributed around your home. It can be piggy-backed to use more than one signal. The unit has an accurate digitally displayed channel selection, Channels 21 to 69.

The SCART input diminishes connection errors and the F-type aerial connectors provide solid and professional connections.

It is PAL-I/BG/K switchable for UK / continental use, and has an adjustable video output level, 65–85 dBµv.

- ✓ Loop Through
- ✓ LED Digital
- ✓ RF Output Level Control
- ✓ Software Switchable
- ✓ PAL B/G PAL-I PAL-K
- ✓ RoHS Compliant



Back view



MOD111

Item Specification

ITEM	VALUE
System	PAL-B/G PAL-I PAL-K
ANT to TV	40-1000MHz: 0-4dB
ANT/TV Port	F (f)
Modulator Output FRE	470-860MHz Adj.
RF Output Level	65-85dBuV
Audio Sub-carrier	4.5MHz 5.5MHz 6.0MHz 6.5MHz
Audio Carrier O/P Level compared to Video Carrier	-12dB or -16dB
Audio/Video Input Port	SCART port
Video Input Impedance	75Ω
Video Input Level	1Vp-p
Audio Input	Recommended 600Ω and 1Vpp
Power Supply	9VDC/300mA

Comes complete with:

- ✓ Power Adaptor (9VDC/300mA)
- ✓ SCART port to SCART port cable
- ✓ User Guide

