



4 Way Booster with IR Bypass

27820BMR



DigiLink
Compatible

27820BMR

4 Way Booster with IR Bypass

Watch and control your Sky™ box in 4 additional rooms

Features & Benefits

- Distributes HD TV, DAB and FM signals
- 2 Inputs - 1x TV signal and 1x DAB/FM
- 4 Outputs - suitable for up to 4 additional TVs/radios
- Integrated IR bypass is compatible with Digi Eye remote control extenders
- 10dB Gain ideal for long cable runs or weak signals
- RED Compliant - updated to improve signal handling



Technical Specification:

| Booster | In | Out | Frequency VHF Signal UHF Signal | Suitable for | Gain | Noise Typ. | Isolation Out/Out | Max Output | IR Bypass | IR Power |
|---------------------|----|-----|---------------------------------------|-----------------------------------|------|---------------|----------------------|---------------|-----------------|------------------|
| 27820BMR SLx4 IR | 2 | 4 | 87-230MHz 470-790MHz | FM/DAB/ TV Ch21-60 Freeview | 10dB | <4dB | 20dB | 90dBμ | 5-30MHz +3dB | 9VDC 15mA SSP |

Distributed By:



01234 26 37 37

01234 26 74 00

sales@philex.co.uk

www.philex.com