



8 Way Booster with IR Bypass

27824BMR



DigiLink
Compatible

27824BMR

8 Way Booster with IR Bypass

Watch and control your Sky™ box in 8 additional rooms

Features & Benefits

- Distributes HD TV, DAB and FM signals
- 2 Inputs - 1x TV signal and 1x DAB/FM
- 8 Outputs - suitable for up to 8 additional TVs/radios
- Integrated IR bypass is compatible with Digi Eye remote control extenders
- Short-circuit protection on outlets to prevent overload
- 10dB Gain ideal for long cable runs or weak signals
- RED Compliant - updated to improve signal handling



Technical Specification:

Booster	In	Out	Frequency VHF Signal UHF Signal	Suitable for	Gain	Noise Typ.	Isolation Out/Out	Max Output	IR Bypass	IR Power
27824BMR SLx8 IR	2	8	87-230MHz 470-790MHz	FM/DAB/ TV Ch21-60 Freeview	10dB	<4dB	20dB	84dBµV	5-30MHz +3dB	9VDC 15mA SSP

Distributed By:



01234 26 37 37

01234 26 74 00

sales@philex.co.uk

www.philex.com