



# 2 Way Booster with IR Bypass

## 27822BMR



DigiLink  
Compatible

27822BMR

## 2 Way Booster with IR Bypass

Watch and control your Sky™ box in 2 additional rooms

### Features & Benefits

- Distributes HD TV or DAB/FM aerial signals
- 2 Outputs - suitable for up to 2 additional TVs or radios
- Integrated IR bypass is compatible with Digi Eye remote control extenders
- Short-circuit protection on outlets to prevent overload
- 20dB Gain ideal for long cable runs or weak signals
- RED Compliant - updated to improve signal handling



### Technical Specification:

Booster	In	Out	Frequency VHF Signal UHF Signal	Suitable for	Gain	Noise Typ.	Isolation Out/Out	Max Output	IR Bypass	IR Power
27822BMR SLx2 IR	1	2	87-790MHz	FM/DAB/ TV Ch21-60 Freeview	17dB	<3dB	12dB	94dBµV	5-30MHz +3dB	9VDC 15mA SSP

Distributed By:



01234 26 37 37

01234 26 74 00

sales@philex.co.uk

www.philex.com