

MAXI PRO-TORCH™

AN AUTHENTIC TREVOR BAYLIS PRODUCT™

BAYLIS®
www.baylisnextgeneration.com
eco windup system

Operating Instructions - Torch

(Please read and keep these instructions).

1. Unfold the Rotary Charge Handle from rear of lamp body and rotate the handle constantly (does not matter which direction), note the green LED Pilot Lamp is lit indicating that charging is in progress. If Pilot Lamp does not light, turn the handle faster. (a winding rate of less than 130 rev/min will not satisfactorily charge the internal power store).
2. 1 minute of winding will enable approx 30 minutes of High Power 5xLED illumination, (2-min winding = 60min use, 3-min winding = 90min use etc. Etc).
3. Press the "ON/OFF" button once to turn on the torch (5-LED), press it again for 1-LED mode, press it again (Stdby Mode). Any unused power will be retained for up to 60 days.

Operating Instructions - Head Lamp

Place Headlamp webbing over head and adjust as necessary. Plug the power lead in to torch Accessory Socket. Press the headlamp's "ON/OFF" button once to turn on (5-LED), press it again for 1-LED mode, press it again for OFF.

Operating Instructions - Phone Charger

1. First, wind the Rotary Charge Handle for 1 minute.
2. Peel forwards the small rubber cover to expose the Accessory Socket.
3. Connect the included charge lead plug into the Accessory Socket and connect the lead to your Mobile Phone's charge socket. The supplied lead fits most Nokia models. The three additional adapters fit many Sony-Ericsson, Nokia & Motorola models. Other phones may be supported - please consult your phone's manufacturer for details. (other adapters are available - visit www.tclproducts.co.uk for details).
4. Wind the Rotary Charge Handle again for at least 1 minute at a steady rate of no less than 130 rev/min while your phone shows a charging indication.
5. Keep the cable connected and make your phone call. If necessary, wind the handle more to prolong the call. Depending upon the condition of the phone's battery, 1 minute of winding will provide approx 6 - 10 minutes of talk time.

Cleaning the torch


Use a moist towel to wipe the surface of the product only. DO NOT use alcohol or other cleaning solvents which may damage the plastic components.

Caution. Do not use this product to charge phone in Petrol Filling Stations, or other areas containing explosive gases.

This torch is "splash-proof" and can be used outside in wet weather. Dry the outside with a towel after use in rain.
DO NOT allow the torch to become submerged in water.

Specifications

Outer Dimensions	160mm(L) x 57.5mm(H) x 58mm (W)
Weight	270g
Internal Power Store	600mAh / 4.8v NiMH
Operating Time 1 LED	1min winding = Approx: 90 min / Full Chrg = Approx: 75hrs
Operating Time 5 LED	1min winding = Approx: 30 min / Full Chrg = Approx: 25Hrs
Lighting Performance	5 x 20,000 mcd InGaP LED's with collimated lens
Phone charging.	> 1500mA
Example Phone Performance	Approx 10min talk after 1min winding / continuous talk possible with intermittent winding



Designed & Produced for Baylis Brands plc by
TCL Products Ltd, Hove, England.
Manufactured in PRC



REF: BA7017