# SCobra®



# LICENSE-FREE WALKIE TALKIES Handfunkgerat Transceptor Talkie Walkie

AM645

Communicates with all other PMR 446 radio

## Up to 8 km range

Compact design with extended range.

### VOX

For hands-free operation.

### **Call Alert**

Provides a recognizable alert for incoming calls.

# **Roger Beep**

Confirmation ton indicates to other it's clear to talk.

# Micro-USB charging capable

rechargable batteries can be charged inside the radio.



Nothing Comes Close to a Cobra®



**Features** 

UHF/FM	Ultra-clear long distance reception.			
8 KM Range	Up to 8 KM range.(Range will vary depending on terrain and conditions.)			
8 Channels	Front panel push buttons provide easy access to all 8 channels.			
121 Privacy Codes	38 CTCSS (Continuous Tone Coded Squelch System) codes and 83 DCS (Digitally Coded Squelch) codes provide a total of 121 privacy codes. 968 privacy combinations are possible when the 8 channels are combined with the 121 privacy codes.			
VOX (Voice Activated Transmission)	User's voice is detected and the radio transmits without the need to press any buttons, freeing the user's hands for other tasks. 5 VOX sensitivity levels allow user to select at which point the radio will detect their voice.			
Scan	Allows user to scan either channels, CTCSS privacy codes within a channel, or DCS codes within a channel to locate conversations in progress.			
Call Alert (5 selectable tones)	Provides up to 5 easily recongizable alert for incoming calls.			
Roger Beep Tone (selectable on/off)	Confirmation tone indicates the completion of the user's transmission, and signals to others it is clear to tall This feature is selectable and can be turned on or off.			
Key Lock	When activated, provides key pad security eliminating accidental channel changes.			
Power Saver	A unique circuit extends the life of your batteries. If there are no transmissions within 10 seconds, the until will automatically switch to battery saver mode.			
Auto Squelch	Automatically shuts off weak transmissions or unwanted noise due to terrain or range constraints.			
LCD Display	Easy to view display provides the radio's status at a glance.			

Radios can also be used with 3 AA alkaline batteries per radio (not included).

Includes a 16 language instruction manual.

High quality band frequencies with no fees.

Secures your microTALK® radio while on the go.

Charges supplied rechargeable batteries inside radios. Accommodates 1 or 2 radios.

Allows use of wall charger, or earphone speaker/microphones (not included) for "hands-free" operation.

Benefits

### **Unit Specifications - General**

6 AA NiMH Rechargeable Batteries

Micro-USB charging cable with "Y" Plug

Speaker/Microphone/Jack

No Licence or Service Fess

**Multilingual Manual** 

**Belt Clip** 

	153.62mm x 61.3mm x 39.46mm (6.05" x 2.41" x 1.55")	SKU#	AM645	"Specifications subject to change without notice"  *All dimensions (H x W x L)*
		UPC	8 56062 00624 1	
Unit Weight	97.5 g. (3.44 oz.) without batteries	RF Output	500 mW	
Channels 8 Channels CH1 = 446 2 = 446 3 = 446 4 = 446 5 = 446 6 = 446 7 = 446	CALL SALE AND	Master Pack Qty	4	
	CH1 = 446.00625 MH 2 = 446.01875	Package Dimension	230mm x 185mm x 56mm (9.05" x 7.28" x 2.20")	
	3 = 446.03125 4 = 446.04375 5 = 446.05625 6 = 446.06875 7 = 446.08125 8 = 446.09375	Batteries	3 AA NiMH rechargeable batteries per radio (included) or can use 3 AA alkaline betteries per radio (not included)	

### 16 Language Manual Includes:







Cobra, microTALK, Nothing Comes Close to a Cobra, and the snake design are registered trademarks of Cobra Electronics Corporation, USA.

Cobra Electronics Corporation is a trademark of Cobra Electronics Corporation, USA.

©2016 Altis Global Limited, Berkeley Lake, GA 30071, USA





<sup>\*</sup> Packaging is made from recyclable materials.