



# Traffic Signal Candle



Special purpose incandescent filament lamp for use in traffic signal equipment.

- 1,000 hour life
- 4,000 switching cycles
- Clear finish
- 2700K warm white
- BC-B22d or SES-E14 cap
- Dimmable
- Internally fused for safety
- Not suitable for household illumination

Product Code	Watts (W)	Volts (V)	Cap	Finish	Colour Temp (K)	Dimensions (mm)		Energy Rating	Order Qty
						Dia	H		
<b>Single Carton</b>									
10062	25W	240	BC-B22d	Clear	2700	35	90		10
10079	25W	240	SES-E14	Clear	2700	35	97		10
10086	40W	240	BC-B22d	Clear	2700	35	90		10
10093	40W	240	SES-E14	Clear	2700	35	97		10
10109	60W	240	BC-B22d	Clear	2700	35	90		10
10116	60W	240	SES-E14	Clear	2700	35	97		10



BC-B22d Cap



SES-E14 Cap



Experts in lighting since 1878