Craft H650R

Pro Series

Product Name: Craft H650R

Description

Product Number: 700H650R

Rechargeable headlamp with lumens and red safety light in the back Press the on/off 1.85 lumens. 2.650 lumens. 3. Off On/off switch in the back to turn on red safety light. Press the buttom 3 sec for displaying battery level. Full battery level 4 green leds. The last led turns red when battery level is very low.

Specifications

Housing material Lens material On/off switch Battery type LED Red LED Colour temperature (Kelvin) Colour rendering index (CRI) Output (lumens) Run time (hours) down to 10% of full lumens Beam distance Adjustable beam - zoom in and out Max charging input Charging time (hours) Charging indicator Battery level indicator Charging port Cable for charger, 1 m (supplied in box) Interchangeable battery Protection class Operating temperature range (Celcius) Headband Clips for helmet Declaration of conformity Additional info

ABS & Aluminum Acrylic, optical Rubberised on/off switch on top 1x18650 Li-lon battery 3,7V 2600mAh 10W In the back 7000 >80 85 / 650 16h (low beam) / 4h (high beam) 200 m Yes - Twist style optical focus system 5V 1000 mAh 4.5h Green leds and 1 Red led Yes Type-C USB USB-C into lamp, USB into charger Yes IK07 / IP65 -10-40 Silicone on the inside Yes - supplied in the box CE and UKCA Fast battery change (interchangeable)







General Information

Lamp weight (g) Lamp dimensions (cm) EAN code box (1 pc) EAN code inner carton = EAN code outer carton = Harmonized standard code

Packaging

Description Box dimensions (cm) Box weight (g) Carton quantity (pcs) Carton size (cm) Carton weight (kg)

Features

Reliable and heavy duty headlamp for the demanding Professional. Red light in the back for high-wis safety on work. The headlamp features a great balance on the head with the batterycompartment in the back.

Fast adjustable headband with silicone stripes for easy helmet mounting. Helmet clips included in the box.

Craft H650R is an upgrade from the popular lamps H2R and later H600R.

181g 3.1 x 6.8 x 5 cm 5703296706308 5703296706315 5703296706322 8513100000

FSC cardboard. Gift box with Elwis PRO design W 12.5 x D 11.55 x H 11 229 g (410g including product) 6pcs / 36pcs 35.5x13.5x23.2 / 43x37.5x49 16.7 kg

Elwis Lighting A/S, Sandtoften 11, 2820 Gentofte, DK

www.elwislighting.com - Tel. +45 70 20 10 24

The following Safety Instructions apply

eral Safety Instructions General Sifety instructions bonot shine in eyes. Do not immerse in water or other liquids. Do not cover the lens when turned on and do not place the product with the lens/light source direct on a surface. Do not operate if the housing, wrime compariment or lens is copen, missing, or damaged. Allow the product to cool down sufficiently before cleaning. Do not use cleaners that contain a branses or solvents. Use of not, stable surfaces. Do not operate with wet hands. Do not disassemble. Do not attempt to repair if damaged. Repairs must only be carried out by the manufacturer or authorized senter representative. Clean with a dy data of dth. Place anot that lighting products generate heat – if the heat excels 60 degrees turn off the product.

Safety instructions - rechargeable products Always inspect the charging plug - it must look dry, clean and undamaged. Only use the supplied charging cable and/or charger. Do not use a modified or damaged charger. Do not try to charge the product if it looks damaged. Do not turn on when charging. Do not leave on The charge the product if it look stampad. Do not not use a monthed or damaged charger. Do not thy to charge the product if it looks damaged. Do not not not work not hargen. Do not laves or charge for over 24 hours. Do not charge below? C, above 40° C are high humidity. Do not leave the product on charge near filmmable material last 1 can cuse a film. Never charge without supervision. Always pay extremely attention to Lion batteries at they can explode. not handled properly, the battery may cuse explosion, leakage of the. Do not expose batteries to direct sunlight. Do not disassemble or modify batteries. Do not apply strong impacts to the battery. Do not get batteries work fees plasteries out of reach of children and animals. Do not place batteries on top of an electromagnetic field. Do not use batteries that work for an astrome yinch period of time. Do not hort-crucit the battery. Do not get to batteries the has can build up. If not handled properly, the battery may cuse explosion, leakage, orfite.

Safety instructions – alkaline batteries Only use new and undamaged batteries. Remove batteries from a device that is not being used for an extended period as they can leak. Never try to charge a non-rechargeable battery

ELWIS

Version 1 06/2022 © Elwis Lighting 2022 All details without obligation