

LEDM07B. LEDM07W

GENERAL INSTRUCTIONS:

These instructions should be read carefully and retained after installation for further reference and maintenance.

SAFETY

- Before installation/maintenance ensure the mains supply is switched off and the circuit fuses/breakers are removed or switched off.
- It is always recommended that a qualified electrician carries out the installation
- Ensure there are no pipes or cables behind the installation surface when drilling fixing holes
- This product is class I rated and must be earthed
- 230V 50Hz
- IP65 Indoor or Outdoor use
- Please recycle this unit.
- This product is equipped with non-replaceable LED Lamps

INSTALLATION

1: Plastic sleeve.

- Cut a hole using the plastic sleeve as a template
- Secure the sleeve into the wall or ground

2: Luminaire

- Thread the pre-installed cable on the luminaire through the cut-out in the plastic sleeve to the position it is to be terminated.
- Align the 2 spring clips on either side of the luminaire with the slots in the top groove of the plastic sleeve
- Push the luminaire into the sleeve and twist to lock into the sleeve
- To remove** reverse the above operation

3: Connecting to the mains cable.

- A cable is pre-wired and installed into the luminaire; this cable may be cut to length if required.
- Connect the pre-installed cable to the mains cable ensuring correct polarity is observed BROWN-LIVE. BLUE-NEUTRAL GREEN/YELLOW – EARTH using a suitable connector block (not supplied).
- Test for correct operation

