

LED LITE™ SMWFAD



13A Tuya Wi-Fi UK Smart Plug In with Timer c/w Energy Monitor

Installation Instructions

SMWFAD is a Tuya WiFi + Bluetooth® Low Energy 13A UK Smart Socket with integrated power metering, designed for remote control, energy monitoring, and smart automation. Supports Tuya Smart and Smart Life apps, voice assistants, and automation with other Tuya-enabled devices.

Technical Features:

Communication: WiFi + Bluetooth® Low Energy
Rated Current: 13A (UK standard socket) max.

Input Voltage: AC 100–240V 50/60Hz

Energy Monitoring: Real-time power measurement and historical data

App Control: Tuya Smart / Smart Life with free push notifications

Functions: Remote ON/OFF, countdown timer, scheduling

Voice Control: Compatible with Amazon Alexa & Google Home

Event Logging: Operation and usage history records

Smart Automation: Scene linkage with other Tuya WiFi devices

Share Control: Multiple users can share and control the smart plug

Product Parameters:

Input Voltage: AC 100–240V 50/60Hz

Rated Current: 13A (UK standard socket)

Communication: WiFi + Bluetooth® Low Energy
 WiFi 2.4Ghz only, 802.11 b/g/n

IP Rating: IP20

Protection Class: Class I

Housing: White PC+ABS

Dimensions: 62 x 59 x 59mm

Operating Temp.: -20°C ~ +50°C

Warranty: 2 Years

Download APP and Add Device

Scan the QR code below to download "Smart Life" or "Tuya Smart" App.



Smart Life APP




Tuya Smart APP

1. Install the APP and register your account




2. Click "Add Device" or select the "+" sign in the upper right corner to add a device



3. Select the socket (Wi-Fi) from the "Electrician" category




4. Enter the correct location WiFi password




5. Check that the indicator light on the socket is flashing quickly and tap on the icon to confirm it in the APP.



6. Wait for the connection to be successful and tap OK.



7. Device added successfully. It can be controlled in the APP now.



If the device appears "Offline" in the app, please wait up to one minute while it connects to your router and the server. When the indicator LED on the device is on, the device is "Online." If the app still shows "Offline," please close the app and reopen it.

Wi-Fi Remote Control and Device Status Updates

Turn the plug on or off by tapping the device icon in the app or pressing the button on the plug. The device status is updated and displayed in the app in real time.

Share Control

Owners can share their devices with other app users. Make sure both users are online in the app when sharing.

Access Intelligent Speaker

Please refer to instructions from the APP to access Amazon Echo or Google Home.

