

LTGL1

Additional RGB Smart Garden Light

IP65 Ⓒ Ⓔ ⓘ Bluetooth



Please read these instructions before commencing installation & retain them for future reference.

Important information

It is recommended that the garden lights are installed by a qualified electrician ensuring the installation complies to current IEE wiring regulations & local building control. We will not accept responsibility for any claims arising from a poor installation.

Important User Advice

- For use with **LTGLK4** RGB Smart Garden Light 4 set only
- This light operates at Safety Extra Low Voltage (24V), via a LED power supply.
- Never connect the light fittings directly to the mains.
- The garden lights are suitable for external use, but must not be submerged in water.
- Do not exceed the LED power supply load.

Installation Procedure

NOTE: The LTGL1 additional light can only be installed as an intermediate lamp in the set.

- Always switch off mains supply before servicing.
- Fix the garden lights in a suitable position.
- Each lamp has 2m of cable (1m on each side) with male and female connectors.
- Connect the 24V supply cable to the LTGLK4 power feed or adjacent lamps using the IP65 connectors:



- You can add up to 2 additional lights to the LTGLK4 set.
- Turn ON power to test correct operation.

- SPECIFICATIONS:**
- Input Voltage: DC 24V
 - Power: 12W
 - 2 metres cable
 - Lamp body material: ABS
 - Colour Temperature: RGB
 - Luminous Flux: 450-750lm

- Beam angle: 45-60 degrees
- IP Rating: IP65
- Control Type: Bluetooth 4.0 Mesh
- Bluetooth Range: up to 10m
- Working Temperature: -25°C~+40°C
- 2 Years Warranty

DIMENSIONS:

