

DIMMERABLE



The World's first family of smooth dimming lamps. The safest on the market with our unique Amalgam fill to protect the environment. Fully compliant with both ROHS and EMC requirements.



Minimum and Maximum Loads on Dimmers of Compact Fluorescent Power

Wattage	250VA	250VA	400VA	400VA	1000VA	1000VA
	Dimmer Min	Dimmer Max	Dimmer Min	Dimmer Max	Dimmer Min	Dimmer Max
Watts	8W	42W	12W	67W	30W	167W

Quantities of DIMMERABLE lamps allowed on Dimmers

Qty on Dimmer	250VA	250VA	400VA	400VA	1000VA	1000VA
	Dimmer Min	Dimmer Max	Dimmer Min	Dimmer Max	Dimmer Min	Dimmer Max
7W	2	6	2	9	5	23
9W	1	4	2	7	4	18
11W	1	3	2	6	3	15
18W	1	2	1	3	2	9

250VA Dimmer based on min load 40VA, 400VA Dimmer based on min load 60VA
1000VA Dimmer based on Min load of 150VA. This data is for guidance only, larger dimmers exist please consult manufacturers specifications for the exact min/max loadings and work out the number of lamps you can use based on 1/5th of min load and 1/6th max load to ensure the correct number for your installation.