



Data Sheet Product Code: JDESM102.BB







Product Description: 2-Gang V-Pro Smart Master WiFi Dimmer 2 x 120W LED (Multi-Way with up to 2 Companion Controllers)

Range: Essential

Finish: Brushed Brass

Product Category: Smart Dimmers

Insert/Knob Colour: Polished Brass Knob

Barcode: 5021575024937

Dimensions: 86x86x48mm

Faceplate Depth: 4mm

Net Weight: 216g

Gross Weight: 218g

Fixing Centres: 60.3mm

Depth from Mounting Face: 23.6mm

Recommended Back Box Depth: 35mm

Operating Voltage: 230v 50Hz

Maximum Load Rating: LED; 120W

Maximum Current Rating: 1.3A

Terminal (Live) Diameter: 3.2mm; Capacity: 3 x 1.5mm<sup>2</sup>

Terminal (Earth) Diameter: 3.3mm; Capacity: 3 x 1.5mm<sup>2</sup>

## Product Features

• Simply connect to the Supla app on your smart device to control the dimmer from your screen at home or aWay for added security and power saving

• Compatible with Google Home or Alexa to dim your lights with your smart assistant

O Ideal for home users, with V-Pro Smart control for intuitive dimming and smart assistant integration

• Direct programming functionality from the Supla app for easy setup. For information on further features, including Group Control, Scheduling, Scene Setting and more, click here.

## Essential Collection

The Essential Collection is the go-to range for unbeatable value. Its sleek, low-profile faceplate features clean lines that add a modern, refined touch to any space, while the visible fixing screws create a simple yet practical aesthetic. The Essential Collection delivers on both affordability and quality, making it the perfect solution for any interior.

## **Brushed Brass Finish**

The Brushed Brass finish combines vintage style with a modern twist to suit both a traditional or modern decor. It is offered with either Black or white inserts and features matching Brass fixing screws. Varilight's decorative wiring accessories are British made and covered by the Varilight lifetime guarantee.

Intended Applications: Indoor Use Only. Domestic lighting circuits including many dimmable LEDs.

Safety Advice: Not suitable for use with non-dimmable fluorescent bulbs and tubes, TRIAC dimmable loads, wire-wound or toroidal transformers or electric motors. Do not overload. Product Must Be Earthed.

Applicable Safety Standard: BS EN 60669-2-1

Commodity Code: 85365005

Declaration of Conformity

Statement of Compliance with UK Connectable Product Security Regulations

All information is subject to change without notice. Errors and omissions excepted. Images are for illustrative purposes only. Individual features and colours may vary. Refer to date of issue to identify latest version. Date of Issue: 04th October 2024 © Doyle & Tratt Products Ltd, Carylls Lea, Faygate, West Sussex, RH12 4SJ, United Kingdom. All rights reserved.