



Data Sheet Product Code: MJM100



Product Features

 ${\pmb \Theta}$ Traditional rotary dimming with Multi-Way operation when used with supplementary controllers

- ⊘ V-Pro Smart Control for intuitive dimming
- Ø Simplified programming system for easy setup
- Ø Full dimming control from up to 3 dimmer locations

♥ This product is not for use with WiFi. Choose Master Dimmer with WiFi for Smartphone Control.. Not suitable for use with Screwless faceplates.

1 YEAR GUARANTEE

BRITISH MADE

Product Description: V-Pro Smart Master Non-WiFi Dimmer 1 x 100W LED (Multi-Way with up to 2 Supplementary Controllers)

Range: Module

Finish: Matrix

Product Category: V-Pro Smart Module

Barcode: 5021575008678

Dimensions: 40x22x44mm (Click here to see full dimensions)

Net Weight: 48g

Gross Weight: 50g

Fixing Centres: N/A

Depth from Mounting Face:

Recommended Back Box Depth: N/A

Operating Voltage: 230v 50Hz

Maximum Load Rating: LED; 100W (Max. 10 LEDs)

Maximum Current Rating: 0.4A

Terminal (Live) Diameter: 3.2mm; Capacity: 3 x 1.5mm²

Intended Applications: Indoor Use Only. Domestic electrical circuits.

 $\label{eq:Safety} \textbf{Safety} \ \textbf{Advice:} \ Not \ suitable \ for \ motors \ or \ fans. \ Not \ suitable \ for \ use \ with \ Screwless \ faceplates. \ Do \ not \ overload.$

Applicable Safety Standard: BS EN 60669-2-1

Commodity Code: 85365005

Declaration of Conformity

All information is subject to change without notice. Errors and omissions excepted. Images are for illustrative purposes only. Individual features and colours may vary. Refer to date of issue to identify latest version.

Date of Issue: 06th February 2022 © Doyle & Tratt Products Ltd, Carylls Lea, Faygate, West Sussex, RH12 4SJ, United Kingdom. All rights reserved.