



Data Sheet Product Code: MJSM100



Product Features

Simply connect to the Supla app on your smart device to control the dimmer from your screen at home or away for added security and power saving

• Compatible with Google Home or Alexa to dim your lights with your smart assistant

O Ideal for home users, with V-Pro Smart control for intuitive dimming and smart assistant integration

• Traditional rotary dimming with Multi-Way operation when used with supplementary controllers, with direct programming functionality from the Supla app for easy setup

• Suitable for all 1-Gang and 3-Gang Matrix Plates, and White Plastic 2-Gang Matrix Kits (WQ2W).

Product Description: V-Pro Smart Master WiFi Dimmer 100W LED (Multi-Way with up to 2 Supplementary Controllers)

Range: Module

Finish: Matrix

Product Category: Smart LED Dimmers

Insert/Knob Colour:

Barcode: 5021575015140

Dimensions: 50x41x45mm (Click here to see full dimensions)

Net Weight: 48g

Gross Weight: 50g

Fixing Centres: N/A

Depth from Mounting Face:

Recommended Back Box Depth: N/A

Operating Voltage: 230v 50Hz

Maximum Load Rating: LED; 100W (Max. 10 LEDs)

Maximum Current Rating: 0.4A

Terminal (Live) Diameter: 3.2mm; Capacity: 3 x 1.5mm²

Intended Applications: Indoor Use Only. Domestic electrical circuits.

Safety Advice: Not suitable for motors or fans.. Do not overload.

Applicable Safety Standard: BS EN 60669-2-1

Commodity Code: 85365005

Declaration of Conformity

All information is subject to change without notice. Errors and omissions excepted. Images are for illustrative purposes only. Individual features and colours may vary. Refer to date of issue to identify latest version.

Date of Issue: 20th April 2023 © Doyle & Tratt Products Ltd, Carylls Lea, Faygate, West Sussex, RH12 4SJ, United Kingdom. All rights reserved.

1 YEAR GUARANTEE

