



# Data Sheet

Product Code: XDYT71S.BC

**Product Description:** 2-Gang (10A Intermediate Switch + 10A 1- or 2-Way Toggle Switch)

**Range:** Urban Screwless

**Finish:** Brushed Copper

**Product Category:** Intermediate Toggle Switch

**Insert/Knob Colour:** Iridium Toggle

**Barcode:** 5021575018721

**Dimensions:** 86x86x36mm

**Faceplate Depth:** 4mm

**Net Weight:** 126g

**Gross Weight:** 128g

**Fixing Centres:** 60.3mm

**Depth from Mounting Face:** 17.4mm

**Recommended Back Box Depth:** 25mm

**Operating Voltage:** 230v 50Hz

**Maximum Load Rating:** 10A

**Maximum Current Rating:** 10A

**Terminal (Live) Diameter:** 3.3mm; **Capacity:** 3 x 1.5mm<sup>2</sup>

**Terminal (Earth) Diameter:** 3.3mm; **Capacity:** 3 x 1.5mm<sup>2</sup>

**Intended Applications:** Indoor Use Only. Domestic lighting circuits.

**Safety Advice:** Product Must Be Earthed.

**Applicable Safety Standard:** BS EN 60669-1


**Commodity Code:** 85365007

Declaration of Conformity



## Product Features

- ☑ 1 x 1- or 2-way switch with 1 x intermediate (3-way) switch alongside
- ☑ Suitable for controlling both mains and low voltage lighting
- ☑ Intermediate switch enables 3-way switching
- ☑ Sleek, low-profile screwless faceplate



10 YEAR GUARANTEE

BRITISH MADE



*All information is subject to change without notice. Errors and omissions excepted. Images are for illustrative purposes only. Individual features and colours may vary. Refer to date of issue to identify latest version.*

*Date of Issue: 06th February 2022 © Doyle & Tratt Products Ltd, Carylls Lea, Faygate, West Sussex, RH12 4SJ, United Kingdom. All rights reserved.*